

PA 1000 Series Mixing Amplifier



Feature

PA 1000 series is a PA Mixing Amplifier with 3 input and have Output Power rating from 15/30/60 Watt.

- 4Ω/8Ω/16Ω/70V/100V system.
- 3 EQ control.
- Priority control: MIC1 > MIC2 & AUX/CD.
- Tabletop

Performance	PA1015	PA1030	PA1060
Max Rated Output Power 1kHz, ≤ 1% THD	15W	30W	60W
Input Sensitivity & Impedance	MIC 1: 1.0mV @250Ω, Balanced MIC 2: 1.0mV @250Ω, Unbalanced AUX: 200mV @47kΩ, Unbalanced CD: 500mV @47kΩ, Unbalanced		
EQ Control	150 Hz ±10dB 1 kHz ±10dB 6 kHz ±10dB		
Frequency Response	60Hz~15kHz, +/-3dB		
S/N Ratio	MIC >60dB AUX/CD >75dB		
Output	4Ω/8Ω/16Ω/70V/100V		
Nominal AC Line Voltage	230V, 50/60Hz		
Operation Temperature / Humidity	-10°C ~ +45°C @ 95% R.H. (Non-Condensing)		
Storage Temperature	-20°C ~ +70°C		
Dimensions (W x D x H)mm	272 x 260 x 75		
Weight	3.8kg	5.0kg	6.0kg



- MIC1-2 level control.
- AUX/CD level control.
- 3 EQ control.
- Master VR controls total outputs level.
- Power ON LED indicator.
- Power ON/OFF switch.

Front Panel

Rear Panel

- MIC1: DIN Balanced input with VOX and Trigger function.
- MIC2: Phone jack Unbalanced input.
- AUX/CD switch: Select AUX or CD input.
- AUX/CD: RCA (MONO) Input.
- Output: 4Ω/8Ω/16Ω/70V/100V Output, Screw connector.
- PRIORITY: Shorted to mute MIC2 and AUX/CD.
- AC Input.

